



# SANYO Semiconductors DATA SHEET

## LV24020LP — Bi-CMOS IC Ultra-compact FM tuner IC for mobile set

### Overview

The LV24020LP is FM tuner IC's that requires absolutely no external components.

They incorporate not only the FM tuner functions as well in a compact VQLP package with dimensions of only 5mm×5mm×0.8mm.

These IC's are simply ideal for incorporating FM tuner functions into mobile phones and other small mobile set where space is always at a premium.

### Functions

- FM FE
- FM IF
- MPX Stereo Decoder
- Tuning

### Features

- No external components
- No alignments necessary
- Fully integrated low IF selectivity and demodulation
- Built in adjacent channel interference total reduction (no 114kHz, no 190kHz)
- Due to new tuning concept, the tuning is independent of the channel spacing
- Very high sensitivity due to integrated low noise RF input amplifier
- Very low power Standby mode. No power switch circuitry required
- MPX output for RDS application
- 3-wire bus interface (Data, Clock, NR-W)
- Digital AFC - Tuner locks to frequency after tuning sequence
- 8 level programmable Soft Mute
- 8 level programmable Stereo Blend
- In combination with the host, fast, low power operation of preset mode, manual search, automatic search and automatic preset store are possible
- Covers all Japanese, European and US bands

■ Any and all SANYO Semiconductor products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO Semiconductor representative nearest you before using any SANYO Semiconductor products described or contained herein in such applications.

■ SANYO Semiconductor assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor products described or contained herein.

**SANYO Semiconductor Co., Ltd.**

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN

# LV24020LP

## Specifications

**Maximum Ratings** at  $T_a = 25^{\circ}\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	$V_{CC}$ max	Analog block supply voltage	6.0	V
	$V_{DD}$ max	Digital block supply voltage	5.0	V
Digital input voltage	$V_{IN1}$ max	Clock, Data, NR_W	$V_{DD}+0.3$	V
	$V_{IN2}$ max	External_clk_in	$V_{DD}+0.3$	V
Allowable power dissipation	$P_d$ max	$T_a \leq 70^{\circ}\text{C}$	140	mW
Operating temperature	$T_{opr}$		-20 to +70	$^{\circ}\text{C}$
Storage temperature	$T_{stg}$		-40 to +125	$^{\circ}\text{C}$

**Operating Condition** at  $T_a = 25^{\circ}\text{C}$

Parameter	Symbol	Conditions	Ratings	Unit
Recommended supply voltage	$V_{CC}$	Analog block supply voltage	3.0	V
	$V_{DD}$	Digital block supply voltage	3.0	V
Operating supply voltage range	$V_{CC}$ op		2.7 to 5.0	V
	$V_{DD}$ op		2.5 to 4.0	V
	$V_{IO}$ op	Interface supply voltage	1.8 to 4.0	V

Note: Power supply voltage  $V_{IO}$  equal  $V_{DD}$ , or  $V_{IO} < V_{DD}$  ( $V_{IO} \leq V_{DD}$ )

**Interface Conditions** at  $T_a = -20$  to  $+70^{\circ}\text{C}$ ,  $V_{SS} = 0\text{V}$

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Supply voltage	$V_{DD}$		2.5		4.0	V
Digital part input	$V_{IH}$	High level input voltage range	$0.7V_{DD}$		$V_{DD}$	V
	$V_{IL}$	Low level input voltage range	0		0.6	V
Digital part output	$I_{OL}$	Low level output current	2.0			mA
	$V_{OL}$	Low level output voltage $I_{OL}=2\text{mA}$			0.6	V
Clock input frequency	fclk	3wire_bus (29pin) clock frequency			0.7	MHz
External clock frequency	fclk_ext	CLK_IN (31pin) frequency	32k		14M	Hz

Note: CLK\_IN (31pin) can input sign wave.

## LV24020LP


**Operating Characteristics** at Ta = 25°C, VCC=3.0V, VDD=3.0V, VOL=14, Soft Mute/Stereo=off

VOL=14 –Block2 register09h Volume\_Bit 3-0 = 0010


Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Operational supply current	ICCA	Analog Block at 60dBμ input The 23pin is measured		14	17	mA
	ICCD	Digital Block at 60dBμ input The 27, 40 pins are measured.	0.2	0.4	0.8	mA
Standby supply current	ICCA	Analog standby mode The 23 pin is measured.		3	30	μA
	ICCD	Digital standby mode The 27, 40 pins are measured.		3	30	μA
FM coverd frq	F_range		76		108	MHz
[FM receiving characteristics ; MONO]: fc=80MHz, fm=1kHz, 22.5kHzdev. soft_stereo, soft_mute, Buss, Treble are all OFF.						
Input limiting voltage	-3dB LS	V <sub>IN</sub> =60dBμ standard for a -3dB input		13	19	dBμV EMF
Practical sensitivity	QS1	for 30dB signal to noise ratio input De-emphasis is 75μs SG open		10	16	dBμV EMF
Practical sensitivity	QS2	for 26dB signal to noise ratio input De-emphasis is 75μs SG close		1.25		μV
Demodulator output level	V <sub>O</sub>	V <sub>IN</sub> =60dBμ, 11pin output level	60	100	140	mV
Channel balance	CB	V <sub>IN</sub> =60dBμ, ratio of 11pin to 12pin output level	-2	0	2	dB
Signal to noise ratio	S/N	V <sub>IN</sub> =60dBμ, 11pin output level	48	58		dB
Total harmonic distortion 1 (MONO)	THD1	V <sub>IN</sub> =60dBμ, 22.5kHzdev, 11pin output		0.4	1.5	%
Total harmonic distortion 2 (MONO)	THD2	V <sub>IN</sub> =60dBμ, 75kHzdev, 11pin output		1.3	3	%
Field strength level	FS	Input level for FS1 to FS2	8	18	27	dBμ
Muting attenuation	Mute-Att	V <sub>IN</sub> =60dBμ, 11pin output level	60	70		dB
[FM receiving characteristics ; STEREO]: fc=80MHz, fm=1kHz, V <sub>IN</sub> =60dBμV, L+R=30% (22.5kHzdev), Pilot=10% (7.5kHzdev)						
Separation	SEP	L-mod, 11pin→12pin output level	20	35		dB
Total harmonic distortion (STEREO)	THD-ST	Main-mod (L+R), 11pin/12pin output, IHF_BPF		0.6	1.8	%

Package Dimensions

unit : mm (typ)  
3302A



Pin Assignment




## LV24020LP

### VQLP40 package Pin Description


Pin	LV24020LP	Description	Remark	DC_bias
1	GND	GND (Analog and Digital GND)		
2	RESERVED		Do not connect	
3	NC			
4	FM-ANT1	Antenna input		
5	FM-ANT2	Antenna GND	Connect to GND	
6	GND	GND (Analog and Digital GND)		
7	NC			
8	NC			
9	NC			
10	NC			
11	LINE-OUT-L	Radio Lch Line-output		1.2V
12	LINE-OUT-R	Radio Rch Line-output		1.2V
13	Package-GND	GND for Package-shield		
14	Package-GND	GND for Package-shield		
15	Package-GND	GND for Package-shield		
16	Package-GND	GND for Package-shield		
17	Package-GND	GND for Package-shield		
18	Package-GND	GND for Package-shield		
19	NC			
20	NC			
21	MPX	MPX-signal output		V <sub>CC</sub> -0.3V
22	NC			
23	V <sub>CC</sub>	Analog supply voltage		
24	NC			
25	V <sub>stabi.</sub>	Stabilizer voltage		2.7V
26	NC			
27	V <sub>DD</sub>	Digital supply voltage		
28	NR_W	Digital interface Read/Write		
29	DATA	Digital interface DATA		
30	CLOCK	Digital interface Clock		
31	CLK_IN	Reference clock-source input for measurement	Connect to GND if not used	
32	NC			
33	Package-GND	GND for Package-shield		
34	Package-GND	GND for Package-shield		
35	Package-GND	GND for Package-shield		
36	Package-GND	GND for Package-shield		
37	Package-GND	GND for Package-shield		
38	Package-GND	GND for Package-shield		
39	NC			
40	V <sub>I/O</sub>	Digital interface supply voltage		

# Block Diagram



ILV000223


# Measurement Circuit



Top view  
VQLP40 package

ILV000224

## Application Circuit



ILV000225

Note1: Vale of External Component is just reference. Please set most suitable value under Acutual\_operation.

Note2: In case of necessary about BPF for FM\_in, Please take Consideration of most suitable\_value.

Note3: We recommend to put R1, R2, R3, R4 for interface between MPU and IC.

Note4: Please put Capacitor Between V<sub>DD</sub> and GND also, put Capacitor Between V<sub>CC</sub> and GND as shown on application.

- Specifications of any and all SANYO Semiconductor products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Semiconductor Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO Semiconductor believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 2006. Specifications and information herein are subject to change without notice.